



Типичные проблемы в отладке RADIUS, PAP и типичных проблемах в отладке RADIUS, PAP и CHAP

Содержание

Введение

Перед началом работы

- Условные обозначения
- Предварительные условия
- Используемые компоненты

Стандартная настройка ПК

- Windows 95
- Windows NT
- Windows 98
- Windows 2000

Конфигурации и примеры отладки

- RADIUS и PAP
- Команды для других версий Cisco IOS
- Примеры отладки - RADIUS и PAP
- Протоколы RADIUS и CHAP
- Команды для других версий Cisco IOS
- Примеры отладок - протоколы RADIUS и CHAP

Команды отладки

Дополнительные сведения

Введение

Этот документ исследует общие проблемы отладки на RADIUS когда используя Протокол проверки пароля (PAP) или Протокол аутентификации квитирования Проблемы (CHAP). Стандартные настройки ПК для Microsoft Windows 95, Windows NT, Windows 98, и Windows 2000 предоставлены, так же как примеры конфигураций и примеры хороших и неудачные отладки.

Перед началом работы

Условные обозначения

Для получения дополнительной информации об условных обозначениях в документации, см. Cisco Условные обозначения технических терминов.

Предварительные условия

Для данного документа отсутствуют определенные предварительные условия.

Используемые компоненты

Сведения в этом документе основаны на Выпусках программного обеспечения CISCO IOS 11.2 и позже.

Сведения, представленные в данном документе, были получены на тестовом оборудовании в специально созданных лабораторных

условиях. Все устройства, описанные в этом документе, были запущены с чистой (стандартной) конфигурацией. При работе с реально функционирующей сетью необходимо полностью осознавать возможные результаты использования всех команд.

Стандартная настройка ПК

Windows 95

Следуйте приведенным ниже инструкциям:

1. В окне передающего Dialup, выберите имя соединения, тогда **File> Properties**.
2. На Вкладке Тип сервера, см. если **Требовать Encrypted Поле пароля** ниже Туре Сервера Модемной связи проверено.
 - Если этот бокс отмечен, то это значит , что PC признает только аутентификацию CHAP.
 - Если этот флажок не поставлен, это означает, что PC принимает идентификация CHAP или PAP.

Windows NT

Следуйте приведенным ниже инструкциям:

1. В окне Dial-Up Networking, выберите имя соединения, и затем выберите **File> Properties**.
2. Проверьте параметры настройки на Вкладке Безопасность:
 - Если **принятие любой идентификации включая ясный текстовое поле** проверено, это означает, что PC принимает PAP или CHAP.
 - Если **Принятие только** флажок **зашифрованной проверки подлинности** поставлен, PC принимает только идентификацию CHAP.

Windows 98

Следуйте приведенным ниже инструкциям:

1. В окне Dial-Up Networking, выберите имя соединения, и затем выберите **Properties**.
2. На вкладке Server Types, проверьте параметры настройки в Продвинутой области Опций:
 - Если **Потребовать поле зашифрованного пароля** необузданно, это означает, что PC принимает идентификация CHAP или PAP.
 - Если **Потребовать поле зашифрованного пароля** проверено, это означает, что PC принимает только идентификацию CHAP.

Windows 2000

Следуйте приведенным ниже инструкциям:

1. В сети и Подключениях удаленного доступа, выберите имя соединения, и затем выберите **Properties**.
2. На Вкладке Безопасность, проверьте параметры настройки в **Продвинутом > Параметры настройки> Разрешают им область протоколов**:

- Если **Незашифрованный пароль (PAP)**, флажок поставлен, PC, принимает PAP.
- Если **Протокол аутентификации квитирования Проблемы (CHAP)** флажок поставлен, PC, принимает CHAP за RFC 1994.
- Если **Microsoft CHAP (MS-CHAP)**, флажок поставлен, PC, принимает версию 1 MS-CHAP и не принимает CHAP за RFC 1994.

Конфигурации и примеры отладки

RADIUS и PAP

Конфигурация - RADIUS и PAP

```

Current configuration:
!
version 11.2
service timestamps debug uptime
no service password-encryption
service udp-small-servers
service tcp-small-servers
!
hostname rtpkrb
!
aaa new-model
!
!---- The following four command lines are specific to
!---- Cisco IOS 11.2 and later, up until 11.3.3.T.
!---- See below this configuration for commands
!---- for other Cisco IOS releases.
!
aaa authentication login default radius local
aaa authentication ppp default if-needed radius local
aaa authorization exec radius if-authenticated
aaa authorization network radius if-authenticated
!
enable secret 5 $1$pkX.$JdAySRE1SbdbDe7bj0wyt0
enable password ww
!
username john password 0 doe
username cse password 0 csecse
ip host rtpkrb 10.31.1.5
ip domain-name RTP.CISCO.COM
ip name-server 171.68.118.103
!
interface Loopback0
ip address 1.1.1.1 255.255.255.0
!
interface Ethernet0
ip address 10.31.1.5 255.255.0.0
no mop enabled
!
interface Serial0
no ip address
no ip mroute-cache
shutdown
!
interface Serial1
no ip address
shutdown
!
interface Async1
ip unnumbered Ethernet0
encapsulation ppp
async mode dedicated
peer default ip address pool async
no cdp enable
ppp authentication pap
!
ip local pool async 15.15.15.15
ip classless
ip route 0.0.0.0 0.0.0.0 10.31.1.1

```

```
!  
snmp-server community public RW  
snmp-server host 171.68.118.100 traps public  
radius-server host 171.68.118.101 auth-port 1645 acct-port 1646  
radius-server key cisco  
!  
line con 0  
line 1  
session-timeout 20  
exec-timeout 20 0  
password ww  
autoselect during-login  
autoselect ppp  
modem InOut  
transport input all  
stopbits 1  
speed 38400  
flowcontrol hardware  
line 2  
modem InOut  
speed 38400  
flowcontrol hardware  
line 3 16  
line aux 0  
line vty 0 4  
exec-timeout 0 0  
password ww  
!  
end
```

Команды для других версий Cisco IOS

Примечание: Для использования этих команд, удалите выделенные команды из конфигурации выше и вставьте их как положено в вашей реализации Cisco IOS.

Cisco IOS 11.3.3. T до 12.0.5. T

```
aaa authen login default radius local  
aaa authen ppp default if-needed radius local  
aaa authorization exec default radius if-authenticated  
aaa authorization network default radius if-authenticated
```

Cisco IOS 12.0.5. T и Позже

```
aaa authen login default group radius local  
aaa authen ppp default if-needed group radius local  
aaa authorization exec default group radius if-authenticated  
aaa authorization network default group radius if-authenticated
```

Примеры отладки - RADIUS и PAP

Примечание: В выходных данных отладки полужирный текст выделяет проблемы в отладке. Обычный текст показывает хорошую отладку.

```
rtpkrb#  
rtpkrb#sho deb  
General OS:  
AAA Authentication debugging is on  
AAA Authorization debugging is on  
PPP:  
PPP authentication debugging is on  
PPP protocol negotiation debugging is on  
Radius protocol debugging is on
```

```
rtpkrb#
4d02h: As1 LCP: I CONFREQ [Closed] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x00001F67 (0x050600001F67)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: Lower layer not up, discarding packet
%LINK-3-UPDOWN: Interface Async1, changed state to up
4d02h: As1 PPP: Treating connection as a dedicated line
4d02h: As1 PPP: Phase is ESTABLISHING, Active Open
4d02h: As1 LCP: O CONFREQ [Closed] id 85 len 24
4d02h: As1 LCP: ACCM 0x000A0000 (0x0206000A0000)
4d02h: As1 LCP: AuthProto PAP (0x0304C023)
4d02h: As1 LCP: MagicNumber 0xF54252D5 (0x0506F54252D5)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
```

**PC insists on doing chap ('accept encrypted authentication only'),
but router is set up for pap:**

```
As1 LCP: I CONFNAK [REQsent] id 98 len 12
As1 LCP: AuthProto 0xC123 (0x0308C12301000001)
As1 LCP: O CONFREQ [REQsent] id 99 len 24
As1 LCP: ACCM 0x000A0000 (0x0206000A0000)
As1 LCP: AuthProto PAP (0x0304C023)
As1 LCP: MagicNumber 0xF54D1AF8 (0x0506F54D1AF8)
As1 LCP: PFC (0x0702)
As1 LCP: ACFC (0x0802)
As1 LCP: I CONFREJ [REQsent] id 99 len 8
As1 LCP: AuthProto PAP (0x0304C023)
As1 PPP: Closing connection because remote won't authenticate
```

```
4d02h: As1 LCP: I CONFACK [REQsent] id 85 len 24
4d02h: As1 LCP: ACCM 0x000A0000 (0x0206000A0000)
4d02h: As1 LCP: AuthProto PAP (0x0304C023)
4d02h: As1 LCP: MagicNumber 0xF54252D5 (0x0506F54252D5)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: I CONFREQ [ACKrcvd] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x00001F67 (0x050600001F67)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: O CONFACK [ACKrcvd] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x00001F67 (0x050600001F67)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: State is Open
4d02h: As1 PPP: Phase is AUTHENTICATING, by this end
4d02h: As1 PAP: I AUTH-REQ id 14 len 19 from "ddunlap"
4d02h: As1 PAP: Authenticating peer ddunlap
4d02h: AAA/AUTHEN: create_user (0x15AD58) user='ddunlap' ruser=''
port='Async1' rem_addr='async' authen_type=PAP service=PPP priv=1
4d02h: AAA/AUTHEN/START (1953436918): port='Async1' list=''
action=LOGIN service=PPP
4d02h: AAA/AUTHEN/START (1953436918): using "default" list
4d02h: AAA/AUTHEN (1953436918): status = UNKNOWN
4d02h: AAA/AUTHEN/START (1953436918): Method=RADIUS
4d02h: RADIUS: Initial Transmit id 7 171.68.118.101:1645,
Access-Request, len 77
4d02h: Attribute 4 6 0A1F0105
4d02h: Attribute 5 6 00000001
4d02h: Attribute 61 6 00000000
4d02h: Attribute 1 9 6464756E
4d02h: Attribute 2 18 7882E0A5
4d02h: Attribute 6 6 00000002
4d02h: Attribute 7 6 00000001
```

**Radius server is down - produces ERROR - since user is not
in local database, failover to local FAILS**

```
As1 PAP: I AUTH-REQ id 16 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=16 already in progress
As1 PAP: I AUTH-REQ id 17 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=17 already in progress
RADIUS: Retransmit id 9
As1 PAP: I AUTH-REQ id 18 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=18 already in progress
As1 PAP: I AUTH-REQ id 19 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=19 already in progress
As1 PAP: I AUTH-REQ id 20 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=20 already in progress
RADIUS: Retransmit id 9
```

```
As1 PAP: I AUTH-REQ id 21 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=21 already in progress
As1 PAP: I AUTH-REQ id 22 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=22 already in progress
RADIUS: Retransmit id 9
As1 PAP: I AUTH-REQ id 23 len 19 from "ddunlap"
As1 AUTH: Duplicate authentication request id=23 already in progress
As1 LCP: I TERMREQ [Open] id 1 len 8 (0x000002CE)
As1 LCP: O TERMACK [Open] id 1 len 4
As1 PPP: Phase is TERMINATING
RADIUS: No response for id 9
%RADIUS-3-ALLDEADSERVER: No active radius servers found. Id 9.
RADIUS: No response from server
AAA/AUTHEN (3025998849): status = ERROR
AAA/AUTHEN/START (3025998849): Method=LOCAL
AAA/AUTHEN (3025998849): status = FAIL
```

Key in router does not match that of server:

```
RADIUS: Received from id 21 171.68.118.101:1645, Access-Reject, len 20
RADIUS: Reply for 21 fails decrypt
```

```
NT client sends 'DOMAIN\user' and Radius server expects 'user':
RADIUS: Received from id 11 171.68.118.101:1645, Access-Reject, len 20
AAA/AUTHEN (1406749115): status = FAIL
As1 PAP: O AUTH-NAK id 25 len 32 msg is "Password validation failure"
As1 PPP: Phase is TERMINATING
As1 LCP: O TERMREQ [Open] id 108 len 4
AAA/AUTHEN: free_user (0xDA520) user='CISCO\ddunlap' ruser=''
port='Async1' rem_addr='async' authen_type=PAP service=PPP priv=1
```

Radius server refuses user because user enters bad password,
or both userid & password are bad:

```
RADIUS: Received from id 12 171.68.118.101:1645, Access-Reject, len 20
AAA/AUTHEN (733718529): status = FAIL
As1 PAP: O AUTH-NAK id 26 len 32 msg is "Password validation failure"
As1 PPP: Phase is TERMINATING
As1 LCP: O TERMREQ [Open] id 111 len 4
AAA/AUTHEN: free_user (0x15B030) user='ddunlap' ruser=''
='Async1' rem_addr='async' authen_type=PAP service=PPP priv=1
```

User passes authentication (i.e. username/password is good)
but fails authorization (profile not set up for Service-Type=Framed &
Framed-Protocol=PPP):

```
RADIUS: Received from id 13 171.68.118.101:1645, Access-Accept, len 20
RADIUS: saved authorization data for user 15AD58 at 15ADF0
AAA/AUTHEN (56862281): status = PASS
AAA/AUTHOR/LCP As1: Authorize LCP
AAA/AUTHOR/LCP: Async1: (959162008): user='cse'
AAA/AUTHOR/LCP: Async1: (959162008): send AV service=ppp
AAA/AUTHOR/LCP: Async1: (959162008): send AV protocol=lcp
AAA/AUTHOR/LCP: Async1: (959162008): Method=RADIUS
RADIUS: no appropriate authorization type for user.
AAA/AUTHOR (959162008): Post authorization status = FAIL
AAA/AUTHOR/LCP As1: Denied
AAA/AUTHEN: free_user (0x15AD58) user='cse' ruser=''
port='Async1' rem_addr='async' authen_type=PAP service=PPP priv=1
As1 PAP: O AUTH-NAK id 27 len 25 msg is "Authorization failed"
```

```
4d02h: RADIUS: Received from id 7 171.68.118.101:1645, Access-Accept, len 32
4d02h: Attribute 6 6 00000002
4d02h: Attribute 7 6 00000001
4d02h: RADIUS: saved authorization data for user 15AD58 at 16C7F4
4d02h: AAA/AUTHEN (1953436918): status = PASS
4d02h: AAA/AUTHOR/LCP As1: Authorize LCP
4d02h: AAA/AUTHOR/LCP: Async1: (2587233868): user='ddunlap'
4d02h: AAA/AUTHOR/LCP: Async1: (2587233868): send AV service=ppp
4d02h: AAA/AUTHOR/LCP: Async1: (2587233868): send AV protocol=lcp
4d02h: AAA/AUTHOR/LCP: Async1: (2587233868): Method=RADIUS
4d02h: AAA/AUTHOR (2587233868): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/LCP As1: Processing AV service=ppp
4d02h: As1 PAP: O AUTH-ACK id 14 len 5
4d02h: As1 PPP: Phase is UP
4d02h: AAA/AUTHOR/FSM As1: (0): Can we start IPCP?
4d02h: AAA/AUTHOR/FSM: Async1: (423372862): user='ddunlap'
4d02h: AAA/AUTHOR/FSM: Async1: (423372862): send AV service=ppp
4d02h: AAA/AUTHOR/FSM: Async1: (423372862): send AV protocol=ip
4d02h: AAA/AUTHOR/FSM: Async1: (423372862): Method=RADIUS
4d02h: AAA/AUTHOR (423372862): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/FSM As1: We can start IPCP
4d02h: As1 IPCP: O CONFREQ [Closed] id 17 len 10
4d02h: As1 IPCP: Address 10.31.1.5 (0x03060A1F0105)
```

```

4d02h: As1 IPCP: I CONFREQ [REQsent] id 1 len 34
4d02h: As1 IPCP: Address 0.0.0.0 (0x030600000000)
4d02h: As1 IPCP: PrimaryDNS 0.0.0.0 (0x810600000000)
4d02h: As1 IPCP: PrimaryWINS 0.0.0.0 (0x820600000000)
4d02h: As1 IPCP: SecondaryDNS 0.0.0.0 (0x830600000000)
4d02h: As1 IPCP: SecondaryWINS 0.0.0.0 (0x840600000000)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 0.0.0.0, we want 0.0.0.0
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 0.0.0.0, we want 0.0.0.0
4d02h: As1 IPCP: Using pool 'async'
4d02h: As1 IPCP: Pool returned 15.15.15.15
4d02h: As1 IPCP: O CONFREQ [REQsent] id 1 len 22
4d02h: As1 IPCP: PrimaryWINS 0.0.0.0 (0x820600000000)
4d02h: As1 IPCP: SecondaryDNS 0.0.0.0 (0x830600000000)
4d02h: As1 IPCP: SecondaryWINS 0.0.0.0 (0x840600000000)
4d02h: As1 IPCP: I CONFACK [REQsent] id 17 len 10
4d02h: As1 IPCP: Address 10.31.1.5 (0x03060A1F0105)
%LINEPROTO-5-UPDOWN: Line protocol on Interface Async1, changed state to up
4d02h: As1 IPCP: I CONFREQ [ACKrcvd] id 2 len 16
4d02h: As1 IPCP: Address 0.0.0.0 (0x030600000000)
4d02h: As1 IPCP: PrimaryDNS 0.0.0.0 (0x810600000000)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 0.0.0.0, we want 15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 0.0.0.0, we want 15.15.15.15
4d02h: As1 IPCP: O CONFNAK [ACKrcvd] id 2 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: As1 IPCP: I CONFREQ [ACKrcvd] id 3 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 15.15.15.15, we want 15.15.15.15
4d02h: AAA/AUTHOR/IPCP: Async1: (4204275250): user='ddunlap'
4d02h: AAA/AUTHOR/IPCP: Async1: (4204275250): send AV service=ppp
4d02h: AAA/AUTHOR/IPCP: Async1: (4204275250): send AV protocol=ip
4d02h: AAA/AUTHOR/IPCP: Async1: (4204275250): send AV addr*15.15.15.15
4d02h: AAA/AUTHOR/IPCP: Async1: (4204275250): Method=RADIUS
4d02h: AAA/AUTHOR (4204275250): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/IPCP As1: Reject 15.15.15.15, using 15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Processing AV addr*15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 15.15.15.15, we want 15.15.15.15
4d02h: As1 IPCP: O CONFACK [ACKrcvd] id 3 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: As1 IPCP: State is Open
4d02h: As1 IPCP: Install route to 15.15.15.15
rtpkrb#

```

Протоколы RADIUS и CHAP

Конфигурация - RADIUS и CHAP

```

Current configuration:
!
version 11.2
service timestamps debug uptime
no service password-encryption
service udp-small-servers
service tcp-small-servers
!
hostname rtpkrb
!
aaa new-model
!

!---- The following four command lines are specific to
!---- Cisco IOS 11.2 and later, up until 11.3.3.T.
!---- See below this configuration for commands
!---- for other Cisco IOS releases.

!
aaa authentication login default radius local
aaa authentication ppp default if-needed radius local
aaa authorization exec radius if-authenticated
aaa authorization network radius if-authenticated

```

```

!
enable secret 5 $1$pkX.$JdAySRE1SbdbDe7bj0wyt0
enable password ww
!
username john password 0 doe
username cse password 0 csecse
ip host rtpkrb 10.31.1.5
ip name-server 171.68.118.103
!
interface Loopback0
ip address 1.1.1.1 255.255.255.0
!
interface Ethernet0
ip address 10.31.1.5 255.255.0.0
no mop enabled
!
interface Serial0
no ip address
no ip mroute-cache
shutdown
!
interface Serial1
no ip address
shutdown
!
interface Async1
ip unnumbered Ethernet0
encapsulation ppp
async mode dedicated
peer default ip address pool async
no cdp enable
ppp authentication chap
!
ip local pool async 15.15.15.15
ip classless
ip route 0.0.0.0 0.0.0.0 10.31.1.1
!
snmp-server community public RW
snmp-server host 171.68.118.100 traps public
radius-server host 171.68.118.101 auth-port 1645 acct-port 1646
radius-server key cisco
!
line con 0
line 1
session-timeout 20
exec-timeout 20 0
password ww
autoselect during-login
autoselect ppp
modem InOut
transport input all
stopbits 1
speed 38400
flowcontrol hardware
line 2
modem InOut
speed 38400
flowcontrol hardware
line 3 16
line aux 0
line vty 0 4
exec-timeout 0 0
password ww
!
end

```

Команды для других версий Cisco IOS

Примечание: Для использования этих команд, удалите выделенные команды из конфигурации выше и вставьте их как положено в вашей реализации Cisco IOS.

Cisco IOS 11.3.3. T до 12.0.5. T

```
aaa authen login default radius local
```

```
aaa authen ppp default if-needed radius local
aaa authorization exec default radius if-authenticated
aaa authorization network default radius if-authenticated
```

Cisco IOS 12.0.5. Т и Позже

```
aaa authen login default group radius local
aaa authen ppp default if-needed group radius local
aaa authorization exec default group radius if-authenticated
aaa authorization network default group radius if-authenticated
```

Примеры отладок - протоколы RADIUS и CHAP

Примечание: В выходных данных отладки, ошибки в отладке выделены курсивным и жирным шрифтом. Обычный текст показывает хорошую отладку.

```
rtpkrb#show debug
General OS:
AAA Authentication debugging is on
AAA Authorization debugging is on
PPP:
PPP authentication debugging is on
PPP protocol negotiation debugging is on
Radius protocol debugging is on
rtpkrb#
4d02h: As1 LCP: I CONFREQ [Closed] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x0000405F (0x05060000405F)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: Lower layer not up, discarding packet
%LINK-3-UPDOWN: Interface Async1, changed state to up
4d02h: As1 PPP: Treating connection as a dedicated line
4d02h: As1 PPP: Phase is ESTABLISHING, Active Open
4d02h: As1 LCP: O CONFREQ [Closed] id 87 len 25
4d02h: As1 LCP: ACCM 0x000A0000 (0x0206000A0000)
4d02h: As1 LCP: AuthProto CHAP (0x0305C22305)
4d02h: As1 LCP: MagicNumber 0xF5445B55 (0x0506F5445B55)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: I CONFACK [REQsent] id 87 len 25
4d02h: As1 LCP: ACCM 0x000A0000 (0x0206000A0000)
4d02h: As1 LCP: AuthProto CHAP (0x0305C22305)
4d02h: As1 LCP: MagicNumber 0xF5445B55 (0x0506F5445B55)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: I CONFREQ [ACKrcvd] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x0000405F (0x05060000405F)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: O CONFACK [ACKrcvd] id 0 len 20
4d02h: As1 LCP: ACCM 0x00000000 (0x020600000000)
4d02h: As1 LCP: MagicNumber 0x0000405F (0x05060000405F)
4d02h: As1 LCP: PFC (0x0702)
4d02h: As1 LCP: ACFC (0x0802)
4d02h: As1 LCP: State is Open
4d02h: As1 PPP: Phase is AUTHENTICATING, by this end
4d02h: As1 CHAP: O CHALLENGE id 11 len 27 from "rtpkrb"
4d02h: As1 CHAP: I RESPONSE id 11 len 28 from "chapadd"
4d02h: AAA/AUTHEN: create_user (0x15AD58) user='chapadd' ruser=''
port='Async1' rem_addr='async' authen_type=CHAP service=PPP priv=1
4d02h: AAA/AUTHEN/START (575703226): port='Async1' list=''
action=LOGIN service=PPP
4d02h: AAA/AUTHEN/START (575703226): using "default" list
4d02h: AAA/AUTHEN (575703226): status = UNKNOWN
4d02h: AAA/AUTHEN/START (575703226): Method=RADIUS
4d02h: RADIUS: Initial Transmit id 8 171.68.118.101:1645,
Access-Request, len 78
4d02h: Attribute 4 6 0A1F0105
4d02h: Attribute 5 6 00000001
4d02h: Attribute 61 6 00000000
```

4d02h: Attribute 1 9 63686170
4d02h: Attribute 3 19 0B895D57
4d02h: Attribute 6 6 00000002
4d02h: Attribute 7 6 00000001

Radius server is down - produces ERROR - since user is not
in local database, failover to local FAILS:

```
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
RADIUS: Retransmit id 15
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
RADIUS: Retransmit id 15
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
RADIUS: Retransmit id 15
As1 CHAP: I RESPONSE id 12 len 28 from "chapadd"
As1 AUTH: Duplicate authentication request id=12 already in progress
As1 LCP: I TERMREQ [Open] id 1 len 8 (0x000002CE)
As1 LCP: O TERMACK [Open] id 1 len 4
As1 PPP: Phase is TERMINATING
RADIUS: id 15, requester hung up.
RADIUS: No response for id 15
RADIUS: No response from server
AAA/AUTHEN (1866705040): status = ERROR
AAA/AUTHEN/START (1866705040): Method=LOCAL
AAA/AUTHEN (1866705040): status = FAIL
As1 CHAP: Unable to validate Response. Username chapadd: Authentication failure
As1 CHAP: O FAILURE id 12 len 26 msg is "Authentication failure"
AAA/AUTHEN: free_user (0x1716B8) user='chapadd' ruser=''
port='Async1' rem_addr='async' authen_type=CHAP service=PPP priv=1
```

Key in router does not match that of server:

```
RADIUS: Received from id 21 171.68.118.101:1645, Access-Reject, len 20
RADIUS: Reply for 21 fails decrypt
```

NT client sends 'DOMAIN\user' and Radius server expects 'user':

```
RADIUS: Received from id 16 171.68.118.101:1645, Access-Reject, len 20
AAA/AUTHEN (2974782384): status = FAIL
As1 CHAP: Unable to validate Response. Username CISCO\chapadd:
Authentication failure
As1 CHAP: O FAILURE id 13 len 26 msg is "Authentication failure"
As1 PPP: Phase is TERMINATING
As1 LCP: O TERMREQ [Open] id 131 len 4
AAA/AUTHEN: free_user (0x171700) user='CISCO\chapadd' ruser=''
port='Async1' rem_addr='async' authen_type=CHAP service=PPP priv=1
```

Radius server refuses user because user is set up for pap,

```
user enters bad password, or both userid & password are bad:
RADIUS: Received from id 17 171.68.118.101:1645, Access-Reject, len 20
AAA/AUTHEN (3898168391): status = FAIL
As1 CHAP: Unable to validate Response. Username ddunlap: Authentication failure
As1 CHAP: O FAILURE id 14 len 26 msg is "Authentication failure"
As1 PPP: Phase is TERMINATING
As1 LCP: O TERMREQ [Open] id 134 len 4
AAA/AUTHEN: free_user (0x1716B8) user='ddunlap' ruser=''
port='Async1' rem_addr='async' authen_type=CHAP service=PPP priv=1
```

User PASSes authentication (i.e. username/password is good)

but FAILs authorization (profile not set up for Service-Type=Framed &
Framed-Protocol=PPP):

```
RADIUS: Received from id 19 171.68.118.101:1645, Access-Accept, len 20
AAA/AUTHEN (2006894701): status = PASS
AAA/AUTHOR/LCP As1: Authorize LCP
AAA/AUTHOR/LCP: Async1: (2370106832): user='noauth'
AAA/AUTHOR/LCP: Async1: (2370106832): send AV service=ppp
AAA/AUTHOR/LCP: Async1: (2370106832): send AV protocol=lcp
AAA/AUTHOR/LCP: Async1: (2370106832): Method=RADIUS
RADIUS: no appropriate authorization type for user.
AAA/AUTHOR (2370106832): Post authorization status = FAIL
AAA/AUTHOR/LCP As1: Denied
```

4d02h: RADIUS: Received from id 8 171.68.118.101:1645, Access-Accept, len 32
4d02h: Attribute 6 6 00000002

```

4d02h: Attribute 7 6 00000001
4d02h: AAA/AUTHEN (575703226): status = PASS
4d02h: AAA/AUTHOR/LCP As1: Authorize LCP
4d02h: AAA/AUTHOR/LCP: Async1: (4143416222): user='chapadd'
4d02h: AAA/AUTHOR/LCP: Async1: (4143416222): send AV service=ppp
4d02h: AAA/AUTHOR/LCP: Async1: (4143416222): send AV protocol=lcp
4d02h: AAA/AUTHOR/LCP: Async1: (4143416222): Method=RADIUS
4d02h: AAA/AUTHOR (4143416222): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/LCP As1: Processing AV service=ppp
4d02h: As1 CHAP: O SUCCESS id 11 len 4
4d02h: As1 PPP: Phase is UP
4d02h: AAA/AUTHOR/FSM As1: (0): Can we start IPCP?
4d02h: AAA/AUTHOR/FSM: Async1: (1916451991): user='chapadd'
4d02h: AAA/AUTHOR/FSM: Async1: (1916451991): send AV service=ppp
4d02h: AAA/AUTHOR/FSM: Async1: (1916451991): send AV protocol=ip
4d02h: AAA/AUTHOR/FSM: Async1: (1916451991): Method=RADIUS
4d02h: AAA/AUTHOR (1916451991): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/FSM As1: We can start IPCP
4d02h: As1 IPCP: O CONFREQ [Closed] id 19 len 10
4d02h: As1 IPCP: Address 10.31.1.5 (0x03060A1F0105)
4d02h: As1 IPCP: I CONFREQ [REQsent] id 1 len 34
4d02h: As1 IPCP: Address 0.0.0.0 (0x030600000000)
4d02h: As1 IPCP: PrimaryDNS 0.0.0.0 (0x810600000000)
4d02h: As1 IPCP: PrimaryWINS 0.0.0.0 (0x820600000000)
4d02h: As1 IPCP: SecondaryDNS 0.0.0.0 (0x830600000000)
4d02h: As1 IPCP: SecondaryWINS 0.0.0.0 (0x840600000000)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 0.0.0.0, we want 0.0.0.0
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 0.0.0.0, we want 0.0.0.0
4d02h: As1 IPCP: Using pool 'async'
4d02h: As1 IPCP: Pool returned 15.15.15.15
4d02h: As1 IPCP: O CONFREQ [REQsent] id 1 len 22
4d02h: As1 IPCP: PrimaryWINS 0.0.0.0 (0x820600000000)
4d02h: As1 IPCP: SecondaryDNS 0.0.0.0 (0x830600000000)
4d02h: As1 IPCP: SecondaryWINS 0.0.0.0 (0x840600000000)
4d02h: As1 IPCP: I CONFACK [REQsent] id 19 len 10
4d02h: As1 IPCP: Address 10.31.1.5 (0x03060A1F0105)
4d02h: As1 IPCP: I CONFREQ [ACKrcvd] id 2 len 16
4d02h: As1 IPCP: Address 0.0.0.0 (0x030600000000)
4d02h: As1 IPCP: PrimaryDNS 0.0.0.0 (0x810600000000)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 0.0.0.0, we want 15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 0.0.0.0, we want 15.15.15.15
4d02h: As1 IPCP: O CONFNAK [ACKrcvd] id 2 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: As1 IPCP: I CONFREQ [ACKrcvd] id 3 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: AAA/AUTHOR/IPCP As1: Start. Her address 15.15.15.15, we want 15.15.15.15
4d02h: AAA/AUTHOR/IPCP: Async1: (1096193147): user='chapadd'
4d02h: AAA/AUTHOR/IPCP: Async1: (1096193147): send AV service=ppp
4d02h: AAA/AUTHOR/IPCP: Async1: (1096193147): send AV protocol=ip
4d02h: AAA/AUTHOR/IPCP: Async1: (1096193147): send AV addr*15.15.15.15
4d02h: AAA/AUTHOR/IPCP: Async1: (1096193147): Method=RADIUS
4d02h: AAA/AUTHOR (1096193147): Post authorization status = PASS_REPL
4d02h: AAA/AUTHOR/IPCP As1: Reject 15.15.15.15, using 15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Processing AV service=ppp
4d02h: AAA/AUTHOR/IPCP As1: Processing AV addr*15.15.15.15
4d02h: AAA/AUTHOR/IPCP As1: Authorization succeeded
4d02h: AAA/AUTHOR/IPCP As1: Done. Her address 15.15.15.15, we want 15.15.15.15
4d02h: As1 IPCP: O CONFACK [ACKrcvd] id 3 len 16
4d02h: As1 IPCP: Address 15.15.15.15 (0x03060F0F0F0F)
4d02h: As1 IPCP: PrimaryDNS 171.68.118.103 (0x8106AB447667)
4d02h: As1 IPCP: State is Open
%LINEPROTO-5-UPDOWN: Line protocol on Interface Async1, changed state to up
4d02h: As1 IPCP: Install route to 15.15.15.15
rtpkrb#

```

Команды отладки

Чтобы привести пример выходных данных отладки в этом документе, использовались следующие команды debug.

Примечание: Перед выполнением команд отладки, пожалуйста см. Важный Информация по Командам Отладки.

- **debug aaa authentication** – отображает сведения о проверке подлинности AAA.
 - **"debug aaa authorization"** - отображение сведений об авторизации AAA.
 - **debug radius** - Подробная отладочная информация Показа связалась с Удаленным Оознавательным Server (RADIUS) Пользователя с наборным телефонным доступом.
 - **"debug ppp negotiation"** – отображаются PPP-пакеты, передаваемые при запуске PPP с согласованием параметров.
-

Дополнительные сведения

- **RADIUS Страница технической поддержки**
 - **Техническая поддержка- Cisco Systems**
-

© 1992-2010 Cisco Systems, Inc. Все права защищены.

Дата генерации PDF файла: Jan 04, 2010

http://www.cisco.com/support/RU/customer/content/103/1039553/radius_pppdebug.shtml
